

CD10369/3/AGB,CD10029/3/SBB Assembly and Installation Instructions

WARNINGS AND CAUTIONS FOR ALL BELOW

1. Fully read these instructions before starting installation, keep installation instructions for future references.
2. Installation is to be performed by a licensed electrician in accordance with the National Electrical Code (NEC) and local authoritative regulations.
3. To prevent electrical shock or hazards ensure electricity is powered off at circuit breaker before re-lamping or wiring of the fixture. Do not install without properly powering off designated area for fixture to be installed.

CAUTION: HEAVY FIXTURE, THE JUNCTION BOX NEEDS TO BE REINFORCED BEFORE INSTALLATION, ALL MOUNTING SCREWS MUST SCREW INTO A MINIMUM OF 1" OF WOOD BEHIND THE DRYWALL. DO NOT MOUNT THIS FIXTURE JUST TO DRYWALL. (All wood that you screw into must be secured to cross beams/ceiling joists behind the drywall).

THIS PRODUCT IS DESIGNED TO BE MOUNTED ON A CORRECTLY INSTALLED STANDARD ROUND OR OCTAGON BOX.

TWO PERSON INSTALLATION

ASSEMBLY INSTRUCTIONS - PENDANT

1. Remove fixture from its original packaging, verify all components and complete a visual inspection.

- A. Metal Concrete Anchors (4)
- B. Mounting Plate (1)
- C. Mounting Screw (2)
- D. Wire Connectors (3)
- E. Canopy Cover (2)
- F. Thread Ring (1)
- G. 3" Rod (1)
- H. 6" Rod (1)
- I. 12" Rod (3)
- J. Fixture Body (1)
- K. Middle Rod (1)
- L. Metal rod (6)
- M. Decorative Nut (6)
- N. Lamp shade (1)
- O. Steel Cable Nut (2)

2. Pre-plan, make sure all Warnings and Cautions above have been completed.
 - If concrete ceiling make sure (A) metal concrete anchors are secure in place.
 - Decide on the hanging height of fixture top to bottom, prepare rods to lengths by removing rods not required.

3. The power cord passes through the middle rod (K) and the fixture body (J). One end of the middle rod (K) is connecting to the top of the fixture body (J), one end is locked on the socket cluster, secure the metal rod (L) on the top cover of the lamp shade (N) with decorative nut (M).

4. Connect the 3" rod (G), 6" rod (H) and 12" rod (I) in sequence, have the power cable run through the connected rod, thread ring (F), canopy cover (E) and mounting plate (B), then screw the connected rod onto fixture body (J) and screw the other end to swivel of mounting plate (B).

5. You are now ready to install the (J) fixture body to the ceiling.
 - Connect the safety cable to a secure strong supporting area. See Illustration below on Page 1.
 - Connect all the wires and ground using (D) wire connectors by twisting matching wires as below.
 - Ø Ground Wire (G, Green or Copper Wire) Green to Green or Copper to Green or Copper to Copper from junction box.
 - Ø Live Wire (L, Black) Black to Black Wire from junction box.
 - Ø Neutral Wire (N, White) White to White Wire from junction box.
 - Ø Once all connected, proceed to next step.

6. Secure the (B) mounting plate to the ceiling by mounting screws and metal concrete anchors accordingly.

7. Raise the (E) canopy cover to the affixed mounting plate (B) until swivel pass through canopy and secure with (F) thread ring.

8. You are now complete and can install bulb(not included) by rotating. (Installation Map on Page 1)

